

Argus 3 Ultra

4K Standalone Battery Camera with 5/2.4 GHz Wi-Fi

- 4K 8MP Ultra HD
- 5/2.4 GHz Dual-Band WiFi
- Color Night Vision

Specifications

Video & Audio	
Image Sensor	1/2.7"CMOS sensor
Resolution	3840 x 2160 (8 megapixels) @15fps
Video Compression	H.265
Field of View	Horizontal: 105° Vertical: 55° Diagonal: 125°
Infrared Night Vision	Up to 10 meters (33ft); LED: 6pcs/0.8w/850nm (Auto-switching with IR-cut filter)
Color Night Vision	With spotlights: 2pcs/2w/6500k
Frame Rate	Main stream: 10fps - 15fps (default: 15fps) Sub stream: 10fps - 15fps (default: 15fps)
Code Rate	Main stream: 1024Kbps - 4096Kbps (default: 3072Kbps) Sub stream: 64Kbps - 672Kbps (default: 672Kbps)
Audio	Two-way audio
Power	
Battery	21.6Wh rechargeable battery (Battery life varies based on settings, usage & temperature.)

Solar	Reolink Solar Panel
Interface	
Power Port	USB Type-C port
SD Card Slot	Supports Max.512GB microSD card
Reset Button	YES
Audio In/Out	Built-in microphone and speaker
Wi-Fi	
Wireless Standard	IEEE 802.11 a/b/g/n
Operating Frequency	2.4GHz/5GHz
Wireless Security	WPA/WPA2
Software	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P
User Access	Max. 12 simultaneous streams (2 main & 10 sub streams)
Other Features	
Smart Alarm	PIR detection; person detection; vehicle detection; animal detection
PIR Detecting Distance	Adjustable up to 10m (33ft)
PIR Detecting Angle	100° horizontal
Recording Modes	Triggered recording
Time Lapse	YES
Smart Home Compatibility	Google Assistant; Alexa
Cloud Storage	Supports Reolink Cloud (available in selected countries)
Working Environment	
Operating Temperature	-10°C~+55°C (14°F~131°F)
Operating Humidity	20% ~ 85%

Weatherproof	IP65
Mechanical	
Dimensions	127 x 90 x 56mm
Weight Battery Included	335g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ .

Gallery & Specs



- 1. Status LED
- 2. Spotlight
- 3. IR LEDs
- 4. Lens
- 5. Daylight Sensor
- 6. Built-in Microphone
- 7. Built-in PIR Sensor



- 1. Reset Hole
- 2. Power Switch
- 3. microSD Card Slot
- 4. USB-C Port
- 5. Mount
- 6. Speaker
- 7. Battery Status LED