

Argus 3 Pro

2K 5/2.4 GHz Wi-Fi Battery Camera with Spotlight

- Person/Vehicle Detection
- 2K+ 5MP Super HD
- 2.4/5 GHz WiFi

Specifications

Video & Audio	
Image Sensor	1/2.7" CMOS sensor
Resolution	2880 × 1620 (5 megapixels) @15fps
Lens	f=2.8mm, F=1.6
Video Compression	H.264/H.265
Field of View	Horizontal:105°,Vertical: 55°
Infrared Night Vision	10m (33ft) (LED: 6pcs/0.8W/850nm)
Color Night Vision	With spotlights: 2pcs/2W/6500K/230 Lumen
Frame Rate	Main stream: 10fps - 15fps (default: 15fps),Sub stream: 10fps - 15fps (default: 15fps)
Code Rate	Main stream: 1024Kbps - 4096Kbps (default: 3072Kbps),Sub stream: 64Kbps - 672Kbps (default: 672Kbps)
Audio	Two-way audio
Power	
Battery	6000mAh rechargeable battery (Battery life varies based on settings, usage & temperature.)

Solar	Reolink Solar Panel (3W)
Interface	
Power Port	USB Type-C port
microSD Card Slot	Supports Max. 512GB microSD card
Reset Button	YES
Audio In/Out	Built-in microphone and speaker
Wireless	
Wireless Standard	IEEE 802.11 a/b/g/n
Operating Frequency	2.4/5 GHz
Wireless Security	WPA-PSK/WPA2-PSK
Software	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P
User Access	Max. 12 simultaneous streams (2 main & 10 sub streams)
Other Features	
Smart Alarm	PIR detection; motion detection; person/vehicle/animal detection
PIR Detection Distance	Adjustable, up to 10m (33ft)
PIR Detection Angle	100° horizontal
Recording Modes	Motion-triggered recording
Time Lapse	YES
Smart Home Compatibility	Google Assistant
Home Hub Compatibility	YES
Cloud Storage	Supports Reolink Cloud (available in selected countries)
Working Environment	
Operating Temperature	-10°C to 55°C (14°F to 131°F)

Operating Humidity	20% to 85%
Weatherproof	IP65
Mechanical	
Dimensions	121 x 90 x 56mm
Weight (Without Bracket)	330g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ .

Gallery & Specs



1. Spotlight
2. Status LED
3. IR LED
4. Lens
5. Daylight Sensor
6. Built-in Mic
7. Built-in PIR Motion Sensor



1. Reset Button
2. Power Switch
3. micro SD Card Slot
4. Bracket
5. Battery Status LED
6. Type-C Port
7. Speaker